



Inner height (D) 12 mm

Single link construction with central anti-friction pivot. Very smooth chain, particularly suitable for small automatic machines like printers, measurements equipment etc.



Technical characteristics when self-supported

| Speed | 10 m/s |
|--------------|---------------------|
| Acceleration | 50 m/s ² |

| Α | В | С | D | R | Weight/m | Chain |
|----|----|----|----|-------------|----------|---------------|
| mm | mm | mm | mm | mm | kg | Part Number |
| 18 | 15 | 12 | 12 | 018-030-040 | 0,13 | 20012 🗆 🗆 * |
| 31 | 15 | 25 | 12 | 018-030-040 | 0,14 | 20025 🗆 🗆 🗠 * |
| 41 | 15 | 35 | 12 | 018-030-040 | 0,15 | 20035 🗆 🗆 🗠 * |
| | | | | | | |

For higher requirements please consult our technical dept.

*Complete the code by inserting the value of the radius (R): Ex. 20012 [] [] []



| R | Н | Ν | М |
|-----|-------------------|---|--|
| mm | mm | mm | mm |
| 018 | 51 | 45 | 95 |
| 030 | 75 | 55 | 130 |
| 040 | 95 | 70 | 165 |
| | mm 018 030 | mm mm 018 51 030 75 | mm mm mm 018 51 45 030 75 55 |

Length of chain (L) Half travel distance $\left(\frac{LS}{2}\right)$ plus length of curve (M)

$$L = \frac{LS}{2} + M$$





Self-Supporting Capacity Diagram

The maximum length of the self-supporting capacity $\left(\frac{LS}{2}\right)$ in relationship to the weight of the cables and hoses contained per linear metre.



The red marking in the diagram area considers the difference of weight between various widths of chain.

For applications with $\frac{LS}{2}$ and weights not included in the area of the diagram showing self-supporting capacity, verify the possible use of support rollers (see page 30).

End Brackets

The end brackets set allows the two ends of the chain to be attached to the equipment.



Fig. A Chain fixed outside the radius. (Fig A)





| Chain | F1 | F |
|-------|----|----|
| Туре | mm | mm |
| 20025 | 13 | 41 |
| 20035 | 23 | 51 |
| | | |

Nylon Type Part Numbers

| Complete Set Assembled | | | | |
|--------------------------|-----------|--|--|--|
| Chain End Brackets | | | | |
| Туре | Set | | | |
| 20012 | AN20012KM | | | |
| 20025 | AN20025KM | | | |
| 20035 | AN20035KM | | | |
| Complete Set Unassembled | | | | |
| Chain End Brackets | | | | |
| Туре | Set | | | |
| 20012 | AN20012K | | | |
| 20025 | AN20025K | | | |
| 20035 | AN20035K | | | |
| | | | | |

Serie Light





For fürther information please consult Brevetti Stendalto's Technical Office